

XA-100XT

Pir Sensor With Standard Bracket, Detection Angle Of 120 Degree



Features

- Low-power 8-bit microprocessor
- Automatic temperature compensation technology
- 5 layers special FRESNEL lens, precise focusing
- LED on/off, pulse counting selectable
- Easy to install, three method selectable
- SMT craft, super anti-EMI and RFI

Technical Specification

Unit Model	XA-100XT
Alarm Output	NC/NO optional, suitable for different alarm control panels
Detecting Distance	12m
Detecting Angle	110°
Working Voltage	DC9~16V
Power Consumption	Quiescent Current: ≤18mA
Alarm Current	≤14mA (at DC 12V)
Working Temperature	-10°C~+50°C
Installation Method	Wall Mounted
Dimension	95 x 55 x 35 (mm)